



SIGNO 6 Specifications

APPLICATIONS:

110V Barrier arm (24V DC Motor) recommended for heavy duty Residential or Commercial applications. Recommended with arms up to 20ft.

OPEN OR CLOSE CYCLE TIME:

from 6 to 10 seconds adjustable.

SHIPPING INFORMATION:

1 box, 140 lbs

NOTE:

ETL approved Available in single and dual setup Manual Emergency Release with Key Battery and Accessories not included

AVAILABLE ACCESSORIES:

- Aluminum arm painted white
- Modular arm plus joint painted white
- Tubular aluminum arm, painted white. Suitable for strong wind areas
- Tubular telescopic arm painted white in aluminum up to 25.5ft with mobile support, counterweight and connector. Shipping length is 20ft;
- Red shockproof rubber strip with caps to close the arm
- Aluminum rack
- Anchorage base with clamps
- · Available Red Light Kit allows identification of arm position
- Red adhesive reflector strips
- Adjustable stand for arms
- Mobile stand for arms
- Breakaway connector
- Photoeye support brackets
- Transmitters with Rolling Code Technology

GENERAL DESCRIPTION:

Simple to install on either right and left hand installations. Adjustable spring tension for various weight, arms and kits. Comes complete with base plate and rectangular arm attachment hardware.

CIRCUIT BOARD:

The Signo6 is shipped with the SIA20 control board.

Features of the control board:

- Adjustable force and speed
- Adjustable auto-close delay
- Inputs for: Exit loops, Safety loops, Keypads, Telephone Entry System, Intercom System and photo eyes
- Plug-in receiver available
- Precision encoder movement
- Flashing lights output
- Easy Programmable PC Board allows you to custom design the settings for each particular job site
- Connection for antenna
- Built-in courtesy light output
- Easy to set arm position with adjustable limits

WARRANTY:

All Apollo & Nice barriers have a two-year limited warranty against manufacturing defects.

FEATURES	Signo 6 + SIA 20
24V DC Inputs	•
Full Systems Capable	•
Auto Reverse sensitivity	•
Auto Close Delay-Adjustable	•
Manual Emergency Release with Key	•
Peripheral Inputs:	
Free Exit	•
Safety Loop	•
Firebox	•
Telephone entry	•
Photoeye	•
Radio Receiver	•
Hold Open Loop	•
Ticket Dispenser	•
Card Reader	•

AVAII	LABLE FR	ем:		